

**DIGITAL ANEMOMETER
MODEL NO.EAM02**



EMC LVD CE

APPLICATION

This anemometer provides instant data such as Air Speed and Air flow in large LCD display with Backlight. This tool has wide measuring range of wind speed from 0.8 ~ 30m/s, CFM: 0 to 99990

This weather device is an ideal tool for windsurfing, sailing and kite flying. You can also use it for industrial and home purposes such as measuring speed and temperature of CPU computer fans, air-conditioners, airflow over the roof or walls

KEY FEATURES

- Easy to set area dimensions are stored in the meter's internal memory for the next power on
- Resolution of 0.01 m/sec
- 20 points average for air flow
- Backlight function
- Auto power off
- Max/min hold and display hold function
- Low battery voltage indication
- Super large(9999 counts) LCD backlight display
- Overflow indication: "OL" will be show in LCD



高度/Height : 165mm
宽度/Width : 85mm
厚度/Thickness : 38mm
重量/Weight : 200g

DIGITAL ANEMOMETER MODEL NO. EAM02

SPECIFICATIONS

* Air Velocity Range:

m/s(meter per second):0.80~30.0, Accuracy:±(2.0% reading + 50)

Ft/m(feet per minute):78~5900,Accuracy:±(2.0% reading +50)

Km/h(kilometer per hour):1.4~108.0,Km/h, Accuracy:±(2.0% reading + 50)

Mile/h(mile per hour):0.9~67.2,Accuracy:±(2.0% reading + 50)

Knots(nautical miles per hour):0.8~58.0,Accuracy:±(2.0% reading + 50)

Ft/s(feet per second):1.3~98.5,accuracy:±(2.0% reading + 50)

* Air Flow Range

CFM:0 to 99990, Area:0 to 9.999ft²

CMM:0 to 99990, Area:0 to 9.999ft²

CMS:0 to 9999,0 to 9.999ft²

* Flow Area Setting

* MAX/MIN Function

* Display backlight

* Auto Power off

* Low battery indication

* Power supply:1x9V 6F 22

* Product Size:168mmx85mmx43mm(6.5"x3.3"x1.5")

* Product weight:200g(0.41b)

* Category: CE



ACCESSORIES

* 1 x Carrying Pouch

* 1 x 9V battery

* 1 x Manual

* Standard factory packing

BESTONE INDUSTRIAL LTD.

Tel: +86 755 82952326, Fax: +86 755 82952326

Web: www.bestone-meter.com

Email: liu@bestone-meter.com

Skype: Bestone-Shirley Liu

WhatsApp: +86 18929394326